

JAIPUR VIDYUT VITRAN NIGAM LIMITED

No. JPD/ Dir (Tech)/SE (RE)/F. 1201/D 260 Dt. 7-5-08

Order


While execution of work for releasing Ag. Connection to ensure proper quality with good workmanship, the following instructions are to be strictly adhered to, regarding installation of transformers, erection of lines, etc. :-

1. If there is only one connection in the existing 25 KVA/40 KVA transformer and capacity of transformer permits, then the new proposed connection will be released from same sub-station by replacing the existing one meter-transformer by two meters transformer.
2. In all other cases not covered by Item No. 1 above, an individual transformer for each Ag. Consumer will be installed as under :-
 - (I) Connection upto 7.5 HP - 10 KVA 3 Phase Transformer on 9 M.Pole.
 - (II) Connection above 7.5 HP & upto to 12.5 HP - 16 KVA 3 Phase transformer on 9 M.Pole.
 - (III) Connection above 12.5 HP up to 20 HP - 25 KVA 3 Phase transformer on 8 M. Pole D. P. structure
 - (IV) Connection above 20 HP & UP to 32 HP - 40 KVA 3 Phase transformer on 8 M. Pole D. P. structure

An Undertaking on the prescribed format as per order No. JPD/CE (Comml.)SE (RE)/F/D. 3371 dated 19.02.08 (REO-187) is compulsorily to be obtained from each & every consumer & kept in the office record safely

3. All 10 KVA and 16 KVA transformers shall be installed in such a way that the transfoemr should be 5 Mtr. (five meters) above from ground level and shall be properly welded with steel structure and also bolted with anti-theft fastners (bolts-nuts) so as to avoid the prossibility of theft.
4. The span for both HT/LT over head line with 8/9 Meters long 200 Kg. working load PCC poles is to be kept 66 meters.
5. There should be proper guarding on all road crossings, telephone line crossings, inter line crossings of all voltages and lines erected near public place and busy area.

my


(K.C. Gupta) 5.5.08
Director (Tech)
Jaipur Discom Jaipur